

## Clock Selection Guide

Notes: S = Standard, A = Available	Model Number													
	120	1094	1095		1200	1201		1202		1205			1206	
	A	B	A	C	B	B	C	B	C	B	C	D	B	C
<b>Peak Accuracy</b>														
100 ns	S					S	S	S	S	S	S	S	S	S
200 ns					S									
250 ns		S	S	S										
<b>Satellite(s)/Inputs</b>														
GPS L1C/A	S	S	S	S	S	S	S	S	S	S	S	S	S	S
GLONASS L1OF	S				S	S	S	S	S	S	S	S	S	S
Galileo E1B/C	S				S	S	S	S	S	S	S	S	S	S
BeiDou B1I	S				S	S	S	S	S	S	S	S	S	S
Event Timer/1 PPS Deviation		S	S	S	S	S	S	S	S	S	S	S	S	S
Power System Frequency and Time Monitor					A	A	A	A	A	S	S	S	S	S
<b>Outputs</b>														
IRIG-B Modulated		S	S	S	S	S	S	S	S	S	S	S	S	S
IRIG-B Unmodulated	S	S	S	S	S	S	S	S	S	S	S	S	S	S
IRIG-B Modified Manchester									S	S				
IRIG-B C37.118-2005	S	S	S	S										
IRIG-B C37.118-2011					S	S	S	S	S	S	S	S	S	S
1 Pulse-Per-Second (PPS)	S	S	S	S	S	S	S	S	S	S	S	S	S	S
Programmable Pulse	S	S	S	S	S	S	S	S	S	S	S	S	S	S
5, 10, 50, 60, 100, 500 PPS										A	A		A	A
1 K, 5 K, 10 K, 50 K, 100 K, 500 K PPS										A	A		A	A
1 M, 5 M, 10 M PPS										A	A		A	A
1 MHz, 5 MHz, 10 MHz (Sinusoid)										A	A		A	A
RS-232, IRIG-J	S	S	S	S	S	S	S	S	S	S	S	S	S	S
RS-422/485 (Transmit)					S	S	S	S	S	S	S	S	S	S
Fault Relay(s)	S	S	S	S	S	S	S	S	S	S	S	S	S	S
Network Time Protocol (NTP)					A	A	A	A	A	S	S	S	S	S
Precision Time Protocol (PTP), IEEE 1588 Server					A	A	A	A	A	S	S	S	S	S
<b>Power</b>														
Universal Power Supply		S			S	S	S	S	S	S	S	S	S	S
Low DC Power Supply		A			A	A	A	A	A	A	A	A	A	A
Surge Withstand Capability		A			S	S	S	S	S	S	S	S	S	S
Dual Power Supply					A	A	A	A	A	A	A	A	A	A
<b>Physical</b>														
Rack Mount		S			S	S	S	S	S	S	S		S	S
DIN Rail Mount			A	A								A		
LCD or VFD Display and/or Keyboard		S			S	S	S	S	S	S	S		S	S
<b>Holdover Oscillator</b>														
Low Drift OCXO						S	S	S	S	S	S	S	S	S
Rubidium Oscillator													S	S
<b>Configuration Method</b>														
Front Panel*		S			S	S	S	S	S					
Utility/Serial Terminal	S		S	S										
Web/SSH										S	S	S	S	S
<b>Warranty</b>														
Limited Ten Year	S	S	S	S	S	S	S	S	S	S	S	S	S	S

\* Options may require configuration not available through the front panel.